

BlueAnt[∞]

COMMUTE 3

Bluetooth Handsfree Kit

Car Speakerphone
(For Bluetooth Mobile Phones)



Table of Contents

1. Product Description	3
2. Product Overview	3
3. Charging	4
4. Power On/Off	4
<i>Power On</i>	4
<i>Power Off</i>	4
5. Selecting language and pairing to your Bluetooth Mobile Phone	5
<i>Pair your phone at first time use</i>	6
<i>Pair an additional phone</i>	6
<i>Automatic Phonebook Transfer</i>	6
6. Manual Phonebook Transfer to the BLUEANT COMMUTE 3	7
7. Phonebook Update	8
8. Installation	9

9. How to use the BLUEANT COMMUTE 3?	10
<i>Useful commands</i>	10
<i>Basic operations</i>	10
Make phone calls	
Answer calls	
End calls	
Reject calls	
Adjust volume	
Transfer a conversation from the phone to the kit	
Transfer a conversation from the kit to the phone	
<i>Advanced functions</i>	12
Music streaming (A2DP)	
Listening to navigation instructions from the GPS of the smartphone	
Three Way calling	
Multipoint	
Connection switching between paired phones	
10. Special Features	16
<i>Automatic Power Off</i>	16
<i>Automatic Power On</i>	16
<i>Erasing all the paired devices and all the phonebooks</i>	17
<i>Easy Pairing</i>	17
<i>Changing the BLUEANT COMMUTE 3 language</i>	18
11. BLUEANT COMMUTE 3 Specifications	19

1. Product Description

The **BLUEANT COMMUTE 3** is a Bluetooth handsfree kit with text to speech and voice answer technologies, it can announce the name of the caller and includes Automatic Phonebook Transfer, Voice Answer, A2DP Music Streaming (as well as Navigation Instructions from the GPS of your smartphone), Multi-Point, Call Waiting and Full DSP (Noise/Echo Cancellation).

The **BLUEANT COMMUTE 3** is designed for an easy and handsfree use. It has superior performances and a powerful and amazing sound quality.

Don't forget: Drive safely and within the law.

Check if the national or local legislation in force in your country does limit the use of mobile phones while driving. It is up to the user of this product to respect the said legislation in the area where they live.

2. Product Overview

(1) Volume Control Button :

- Turn clockwise to increase the volume, anticlockwise to decrease the volume
- Press for 1 second to pick up a call
- Press for 1 second to hang up
- In stand-by mode, press for 3 seconds to redial the latest phone number dialled
- In stand-by mode, press for 1 second to activate voice dialling function of the connected phone (*)

(2) Bluetooth Indicator :

- Steady blue : in communication
- Blinking blue : connected / paired / on
- Led turns red : low battery
- Blinking red / blue : pairing mode

(4) Microphone

(5) Charger Plug (Micro-USB)

(6) Charge Indicator :

- Steady orange : charging
- Steady green : battery full

(7) On / Off Button :

- Press for 1 second to switch the unit ON or OFF

(8) End / Reject Button and Phonebook Update :

- Press for 1 second to end a call
- Press for 1 second to reject a call
- Press for 5 seconds to start an automatic phonebook update (in case you've added or renamed some contacts)

(3) Speakers



3. Charging

Your **BLUEANT COMMUTE 3** announces the battery level when you turn it on. If the **BLUEANT COMMUTE 3** says "Battery low", the **Bluetooth indicator (2)** will turn blinking red. The kit needs to be charged.

1. Connect the charger's plug into the **Charger Port (5)** of the **BLUEANT COMMUTE 3**. Connect the charger to an external power source.

Charge Indicator (6) Status:

Steady Orange: **Charging**

Steady Green: **Battery Full**

2. When fully charged, disconnect the charger.

4. Power On/Off

1. Power On:

Press the **On/Off Button (7)** for 1 second. A starting notification sound will be heard and the kit will announce its battery level then say, **"Connected to phone"** (or, if phone not available: **"No phone found"**). The **Bluetooth Indicator (2)** will turn blinking blue.

2. Power Off:

Press the **On/Off Button (7)** for 1 second. An ending notification sound will be heard and the kit will say, **"BLUEANT COMMUTE 3 powering down."** The **Bluetooth Indicator (2)** will turn off.

5. Selecting language and Pairing to your Bluetooth Mobile Phone

BLUEANT COMMUTE 3 needs to be paired to your Bluetooth mobile phone to create the link or audio connection between the two. Pairing should be done only at the first connection to a phone.

1. Pair your phone at first time use

For first time use, when you will turn the **BLUEANT COMMUTE 3** on, it will instruct you to select the preferred language to use.

Note: There are 12 languages featured in the **BLUEANT COMMUTE 3**, British English, American English, French, Italian, German, Spanish, Mexican Spanish, Brazilian Portuguese, Chinese, Russian, Japanese and Polish.

The kit will say, “**Press Volume Control Button (1) to select British English.**” The **BLUEANT COMMUTE 3** will cycle through all available languages. Short press the **Volume Control Button (1)** when you hear your language.

If the British English language is chosen, the kit will say, “**British English selected. From phone's Bluetooth menu, search for devices then select BLUEANT COMMUTE 3. Enter pin code 0000 if requested.**” This means the kit is now ready to be paired. Access the Bluetooth menu of your phone then execute a Bluetooth search. Then follow the handsfree kit and phone prompts to pair the **BLUEANT COMMUTE 3**.

IMPORTANT: Accept any connection or pairing prompt on your phone and follow the voice prompts to pair the **BLUEANT COMMUTE 3** with your mobile phone. The pairing code is **0000** (four zero's).

Pair an additional phone

Turn on the **BLUEANT COMMUTE 3**.

Disconnect any connected phone by disabling its Bluetooth function or by turning the phone off.

The **BLUEANT COMMUTE 3** is now discoverable and pairable. You can connect any phone you want by executing a Bluetooth search on the phone you want to connect, then selecting **BLUEANT COMMUTE 3** in the list of found Bluetooth devices.

Note: Accept any connection or pairing prompt on your phone and follow the voice prompts to pair the **BLUEANT COMMUTE 3** with your mobile phone. The pairing code is **0000** (four zero's).

2. Automatic Phonebook Transfer

After the successful pairing, a voice will announce, **“Pairing successful to phone. Loading Phonebook. Please wait.” “Connected to phone.” “Accept any connection request on phone.”** The handsfree kit will start downloading your phonebook contacts. The number of contacts will be announced, as download is ongoing.

With Android phones, accept any request at the top of the screen's phone.

Note: Accept any request (Connection...?, allow phonebook access...?, DUN...?) prompt on your phone.

IMPORTANT NOTICE: Some Symbian phones do not support automatic Phonebook downloading. In this case, the kit will say **“Automatic transfer not supported by phone. To send your phonebook manually please mark the contacts in your phone, send the businesses cards or transfer the contacts via Bluetooth to the BLUEANT. To use your kit immediately without phonebook transfer, press the Volume Control.** Proceed to **section 6. Manual Phonebook Transfer to the BLUEANT COMMUTE 3** to transfer the phonebook manually or press the Volume Control Button (1) of the COMMUTE 3 to connect the kit to the phone without any phonebook transfer.

When the download is complete, the kit will say, “**Loading Phonebook Successful. BLUEANT COMMUTE 3 ready.**” the handsfree kit is now ready to use.

Note: After pairing, most phones automatically connect to the kit. With some phones you will need to connect to the kit manually. Go to **Bluetooth > Paired devices > highlight BLUEANT COMMUTE 3 > press Options > then press Connect.** Or press the **Volume Control Button (1)** to connect to handsfree kit.

6. Manual Phonebook Transfer to the BLUEANT COMMUTE 3

If the automatic phonebook transfer failed, you can send or transfer your contacts to the **BLUEANT COMMUTE 3** by sending them via Bluetooth.

IMPORTANT:

This procedure will only work right after the pairing (see **section 5. Selecting language and Pairing to your Bluetooth Mobile Phone**) or right after the phonebook update (see **section 7. Phonebook Update**).

Note: For some phones, if you modify the phonebook; to consider the changes, you might need to turn off the phone then turn it on. Once the phone is connected to the **BLUEANT COMMUTE 3**, execute the Manual Transfer of the Phonebook.

Procedure:


1. There are two ways to proceed with the procedure depending on your phone model.
 - ▶ The common way is:
 - a. Go to the *Phonebook* of your phone.
 - b. Choose a contact or group of contacts you want to send to the kit.

Note: Choose “Mark all” (if this option is available in your phone) to be able to send all contacts at one time. However, there are phones that do not support sending all contacts at one time. Thus, you need to send them one by one.

- c. Choose to send the contacts via Bluetooth > select **BLUEANT COMMUTE 3**

Note: On some phones, SIM contacts transfer is impossible.

► The other way is:

- a. Go to *Options* icon in your phone.
- b. Choose *Bluetooth* > Highlight **BLUEANT COMMUTE 3**  > press key> Choose *Transfer Address Book*.
- c. Choose to transfer via Bluetooth > select **BLUEANT COMMUTE 3**.

2. **“Loading phonebook. Accept any connection request on phone. Please wait.”** will then be announced on the kit. The number of contacts will be announced, as download is ongoing.

Note: Accept any request (*Connection...?*, allow phonebook access...?, *DUN...?*) prompt on your phone.

3. You have two minutes to add a new contact or new group of contacts. Then, the **BLUEANT COMMUTE 3** will say, **“Connected to phone.”** The handsfree kit is now ready to use.

With Android phones, accept any request at the top of the screen's phone.

Note: For some phones, you may need to accept any connection prompt on the phone before the reconnection takes place.

7. Phonebook Update

If you renamed or added a contact in your phone, you can refresh the phonebook of the **BLUEANT COMMUTE 3** for the kit to recognize the change.

Note: For some phones, if you modify the phonebook, to consider the changes, you might need to turn off the phone then turn it on. Once the phone is connected to the **BLUEANT COMMUTE 3**, execute the Phonebook Update.

Procedure:

1. Ensure that the phone is connected to the kit. In standby mode, long press the **End / Reject button and Phonebook update (8)** for 5 seconds.

2. **“Loading phonebook. Please wait. Accept any connection request on phone.”** will be announced. The number of contacts will be announced while the download is ongoing.

Note: Accept any request (Connection...?, allow phonebook access...?, DUN...?) prompt on your phone.

With Android phones, accept any request at the top of the screen's phone.

IMPORTANT NOTICE: Some Symbian phones do not support automatic Phonebook downloading. In this case, the kit will say **“Automatic transfer not supported by phone. To send your phonebook manually please mark the contacts in your phone, send the businesses cards or transfer the contacts via Bluetooth to the BLUEANT. To use your kit immediately without phonebook transfer, press the Volume Control. Proceed to section 6. Manual Phonebook Transfer to the BLUEANT COMMUTE 3 to transfer the phonebook manually or press the Volume Control Button (1) of the BLUEANT COMMUTE 3 to connect the kit to the phone without any phonebook transfer.**

3. When the download is complete, the **BLUEANT COMMUTE 3** will say **“Loading Phonebook Successful. BLUEANT COMMUTE 3 ready.”** The handsfree kit is now ready to use.

Note: For some phones, you may need to accept any connection prompt on the phone before reconnection takes place.

8. Installation

Fix the metal clip of **BLUEANT COMMUTE 3** on the sun visor.

Attach the **magnetic** back of **BLUEANT COMMUTE 3** to the fixed metal clip. The **BLUEANT COMMUTE 3** must be placed in such a way that its **microphone (4)** is directed to the mouth of the user.

9. How to use the BLUEANT COMMUTE 3?

IMPORTANT:

The kit needs to be 'paired' to your Bluetooth mobile phone first, before you can use the following functions. See **section 5. Selecting language and Pairing to your Bluetooth Mobile Phone.**

Make Phone calls

Use your voice to make phone calls

Press the **Volume Control button (1)** for one second.

And the kit will activate the voice dial features on your phone. Via the handsfree a beep will be heard to prompt you to say the voice tag of the contact to call. Say the voice tag exactly as how you recorded it. The voice tag will be played back to you and then the phone will dial the number automatically.

This function can be used if supported by connected phone. Please note efficiency depends only on connected phone.

Note: *Before using this feature, make sure that the voice dialing function of your phone is activated. Some phones need to have at least one voice tag recorded in the phone's memory, not on the SIM card! (Kindly refer to your phone's manual.)*

Redial last number

In stand by mode, press the **Volume Control button (1)** for 3 seconds to redial the last number you called.

Use your phone to make calls

You can also make calls manually using your phone. The audio will automatically be transferred to the handsfree kit.

Answer Calls

When the phone rings, the **BLUEANT COMMUTE 3** will read out the caller's name or number. After the beep, say **"OK"**. Or press the **Volume Control button (1)** for 1 second to answer the call. The incoming call is answered and the audio is heard through the handsfree kit.

End Calls

During an ongoing call, press the **End / Reject button and Phonebook update (8)** for 1 second to end the call.

Reject Calls

When the phone rings, **BLUEANT COMMUTE 3** will read out the caller's name or number. Press the **End / Reject button and Phonebook update (8)** for 1 second. The incoming call will be rejected.

Adjust Volume

Increase or decrease the volume by turning the **Volume Control button (1)** until the desired level is reached. When the maximum volume is reached, **"Maximum Volume"** will be announced on the kit.

Transfer the audio conversation from the phone to the kit

Press and hold the **Volume Control button (1)** for 3 seconds and the audio will automatically be transferred to the handsfree kit.

Transfer the audio conversation from the kit to the phone

Press and hold the **Volume Control button (1)** for 3 seconds and the audio will automatically be transferred to the phone.

1. Advanced functions

Music streaming (A2DP)

If your phone supports **A2DP** (Advance Audio Distribution Profile), you can stream music from your phone to the **BLUEANT COMMUTE 3**.

To stream Music, Play/Pause:

Go to your phone's music player and play a track via A/V Bluetooth. (See your phone's manual). Your music will be played through the **BLUEANT COMMUTE 3**.

To adjust the Volume:

Increase or decrease the volume by turning the **Volume Control button (1)** until the desired level is reached.

***Note:** If you receive an incoming call while listening to music, the streaming will automatically be paused, muted or stopped until you end or reject the call. During the call, the conversation will be done through the handsfree kit. On some phones, when the call is ended or rejected, you will need to restart the music by playing it manually.*

Listening to navigation instructions from the GPS of your smartphone (A2DP)

If your phone supports **A2DP** (Advance Audio Distribution Profile) **and has an internal GPS**, you can listen to navigation instructions from the GPS of your phone to the **BLUEANT COMMUTE 3**. Please refer the user's manual of your phone.

To adjust the Volume:

Increase or decrease the volume by turning the **Volume Control button (1)** until the desired level is reached.

***Note:** If you receive an incoming call while listening to navigation instructions, the streaming will automatically be stopped until you end or reject the call. During the call, the conversation will be done through the handsfree kit. On some phones, when the call is ended or rejected, you will need to restart the navigation of the phone manually.*

Three Way calling

IMPORTANT: Before using this feature, make sure that your phone and the phone network support call waiting.

If you receive a call during an ongoing call, a low beep will be heard from the **BLUEANT COMMUTE 3**.

To end the current call and accept the second incoming call:

Short press the **Volume Control button (1)**; the current call will be ended and the second call accepted. The audio of the second call will automatically be heard through the handsfree kit.

To place the current call on-hold and accept the second incoming call:

Double short press the **Volume Control button (1)**; it will hold the current call and answer the second call. The audio of the second call will automatically be heard through the handsfree kit.

To swap the current call with the held call:

Double short press the **Volume Control button (1)**; it will automatically put on-hold the current call and activate the on-hold call. The audio of the activated held call will be heard through the handsfree kit.

Note: For some phones, you will need to go to the phone call menu before executing the audio swapping between the current and the held call.

To end the current call and retrieve the held call:

Short press the **Volume Control button (1)**; it will end the current call and activate the on-hold call. The audio of the activated held call will automatically be heard through the handsfree kit.

Note: For some phones, you will need to double short press the **Volume Control button (1)** to retrieve the held call.

Multipoint

The **BLUEANT COMMUTE 3** can simultaneously connect to 2 Bluetooth devices. The **BLUEANT COMMUTE 3** is active on both mobile phones. User actions (voice dial, redial) will control the primary phone, but an incoming call on any of the two phones can be accepted or rejected from the **BLUEANT COMMUTE 3**.

Multi-Point Pairing Procedure:

1. Turn off the handsfree kit by pressing the **On/Off button (7)** until the LED flashes red.
2. Pair the additional phone referring to **2. Pair an additional phone in the section 5**. This phone will now be the primary phone.
3. Then connect 1st phone manually after the 2nd phone successfully paired.

Using Multi-Point:

Refer to **2. Basic operations in the section 9**.

Note:

- Voice dial and re-dial will be done using the primary phone only.
- You can accept, reject or ignore calls from any of the two phones.

When you already have an ongoing call on the 1st phone, if you receive a call on the 2nd phone, you will hear a special ringtone during the ongoing communication.

Note: The Voice answer function is disabled when you have an ongoing call. This allows you to end the first call before you answer the second call.

To end the current call and accept the second incoming call:

Short press the **Volume Control button (1)**; it will end the current call and accept the second call. The audio of the second call will automatically be heard through the handsfree kit.

To place the current call on-hold and accept the second incoming call:

Double short press the **Volume Control button (1)**; it will hold the current call and answer the second call. The audio of the second call will automatically be heard through the handsfree kit.

To swap the current call with the held call:

Double short press the **Volume Control button (1)**; it will automatically put on-hold the current call and activate the held call. The audio for the activated held call will be heard through the handsfree kit.

To end the current call and retrieve the held call:

Short press the **Volume Control button (1)**; it will end the current call and activate the on-hold call. The audio for the activated held call will automatically be heard through the handsfree kit.

Note: For some phones, you will need to double short press the **Volume Control button (1)** to retrieve the held call.

To accept incoming calls on a phone while the other phone is playing A2DP music:

If Phone1 receives an incoming call while Phone2 is playing A2DP music through the handsfree kit, the music will automatically be paused, muted or stopped. The Phone1 incoming call will ring through the handsfree kit.

Short press the **Volume Control button (1)** will accept phone1's incoming call, and the audio will be heard through the handsfree kit. When phone1's call is ended or rejected, phone2's music streaming will automatically resume (the A2DP music will be streamed through the handsfree kit).

Note: On some phones, you will need to restart the music by playing it manually.

To accept incoming calls on a phone while the other phone is listening to navigation instructions:

If Phone1 receives an incoming call while Phone2 is listening to navigation instructions through the handsfree kit, the navigation instructions will automatically be stopped. The Phone1 incoming call will ring through the handsfree kit.

Short press the **Volume Control button (1)** will accept phone1's incoming call, and the audio will be heard through the handsfree kit. When phone1's call is ended or rejected, phone2's navigation instructions will automatically resume.

Note: On some phones, you will need to restart the navigation by playing it manually.

Connection switching between paired phones

The **BLUEANT COMMUTE 3** always maintains a maximum of 8 phones in its memory. An additional pairing will automatically delete the phone that has not been used for the longest time. Any deleted phone needs to be paired again before it can be used.

You can easily switch to any of the paired phones by:

1. Disconnecting one of the 2 connected phones using the "Active devices" in the Bluetooth menu of that phone.
2. Connecting the handsfree kit to the desired phone by using the "Paired devices" in the Bluetooth menu of that phone.

10. Special Features

Automatic Power Off:

If you leave your car, the handsfree kit will automatically **power off** after 5 minutes without any detected phone connection.

Automatic Power On:

The handsfree kit will automatically **power on** and reconnect to your phone when you get back in your car.

Note: *This automatic reconnection might take few seconds after getting back into the Bluetooth range.*

Erasing all the paired devices and all the phonebooks:

The **BLUEANT COMMUTE 3** must be set to **pairing mode** (from off, press and hold the **On / Off button (7)** until the **Bluetooth indicator (2)** turns blinking red/blue. The kit is now on pairing mode.)

Once your kit is on **pairing mode** ignore the vocal procedure and press and hold the **End / Reject button and Phonebook update (8)** for 5 seconds until a distinctive melody is heard on the kit. Now, all the paired phones and the phonebook are erased. You can proceed to a new pairing following the ongoing procedure or referring to **section 5. Selecting language and pairing to your mobile phone.**

Easy Pairing:

The easy pairing is a pairing procedure, which allows you to pair your phone to the handsfree kit without executing any Bluetooth search from your phone.

IMPORTANT: *Make sure that your phone's Bluetooth mode is active and discoverable (see your phone's manual). Then place your phone and the **BLUEANT COMMUTE** close to each other.*

The **BLUEANT COMMUTE 3** must be set to **pairing mode** (from off, press and hold the **On / Off button (7)** until the **Bluetooth indicator (2)** turns blinking red/blue. The kit is now on pairing mode.)

Once your kit is on **pairing mode** the kit will say, "**Press Volume Control (1) to select British English.**" The **BLUEANT COMMUTE 3** will cycle through all available languages. Short press the **Volume Control button (3)** when you hear your language.

Once your preferred language is selected, ignore the vocal procedure and directly short press the **Volume Control button (1)**. The kit will say, "**Easy Pairing**" and will process your phone research (beeps will be heard). Accept any connection request on your phone. Enter the pin code "**0000**" if requested.

For the next steps, please refer to **section 5** at **3. Automatic Phonebook Transfer.**

Changing the BLUEANT COMMUTE 3 Language:

The **BLUEANT COMMUTE 3** must be set to **pairing mode** (from off, press and hold the **On / Off button (7)** until the **Bluetooth indicator (2)** turns blinking red/blue. The kit is now on pairing mode.).

Once your kit is on **pairing mode** the kit will say, “**Press Volume Control (1) to select British English.**” The **BLUEANT COMMUTE 3** will cycle through all available languages. Short press the **Volume Control button (1)** when you hear your language.

Ignore the vocal procedure and turn off the kit by pressing the **On / Off button (7)** for 1 second. The next time you will turn on the kit, the selected language will be active.

11. BLUEANT COMMUTE 3 Specifications

Bluetooth Compliance:	Bluetooth version 3.0 specifications
Supported Bluetooth Profiles:	A2DP/Supports headset and handsfree profiles with automatic detection
Operating Range:	Up to 10 meters
Frequency:	2.4 GHz
Talk Time:	Up to 20 hours
Stand-by time:	Up to 1000 hours
Charging Time:	3 hours
Battery Type:	Rechargeable Lithium Ion
Special Features	<ul style="list-style-type: none">▪ Voice to announce Caller ID, Bluetooth device status and instruction guides in 12 languages (British English, American English, French, Italian, German, Spanish, Mexican Spanish, Brazilian Portuguese, Chinese, Russian, Japanese and Polish)▪ Full Duplex▪ Full DSP Noise Cancellation / Echo Cancellation▪ Easy Pairing▪ Digital Volume Control▪ Voice answer (say "OK" to answer a call)▪ Voice Recognition Dialing (If phone supports)▪ Last Call Redial▪ Can also be charged directly from a computer via USB Cable (included)▪ Music Streaming (A2DP)▪ Multipoint▪ Three Way Calling▪ Auto Power Off▪ Auto Power On▪ High speakers V array technology▪ Firmware updatable via USB cable (not included)▪ Full Automatic reconnection
Multipoint:	Can be paired up to 8 devices Maximum of 2 phones connected at a time
Installation:	Quick fixation on sun visor via metal clip
Dimensions (mm):	125 x 61 x 26 mm
Weight:	111 g

Disclaimer

Greatest care has been taken to provide accurate and complete information in this manual. The manufacturer is not liable for errors and missing information. The manufacturer reserves the right to change and improve functions and specifications of the product without notice. Duplication, transmission of part or all of this manual without consent of the manufacturer is prohibited. All rights reserved.

The Bluetooth word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by BlueAnt Wireless Pty Ltd is under license. Other trademarks and trade names are those of their respective owners.

Correct Disposal of This Product (Waste Electrical & Electronic Equipment)



(Applicable in the European Union and other European countries with separate collection systems). This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources. Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take this item for environmentally safe recycling. Business users should contact their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal. This product has an embedded, non-replaceable battery, do not attempt to open the product or remove the battery as this may cause injury and damage the product. Please contact the local recycling facility for removal of the battery. The embedded, non-replaceable battery is designed to last the life time of the product.

Hereby, BlueAnt Wireless Pty Ltd declares that the BlueAnt Commute3, MODEL COMMUTE3, is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC of the European Parliament and of the Council of 9 March 1999 on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity.

C € 0560



The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by BlueAnt Wireless Pty Ltd is under license. Other trademarks and trade names are those of their respective owners.

Federal Communications Commission (FCC) Statement
Industry Canada (IC) Statement

15.21

You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

15.105(b)

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC/IC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures :

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Operation is subject to the following two conditions :

- 1) This device may not cause interference and
- 2) This device must accept any interference, including interference that may cause undesired operation of the device.

FCC/IC RF Radiation Exposure Statement :

This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

AUSTRALIAN CONSUMER LAW

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if goods fail to be of acceptable quality and the failure does not amount to a major failure.

For warranty and technical support please visit

www.blueantwireless.com

or call 1300 669 049

BlueAnt Wireless,

1-7 Weston St, Brunswick, Victoria, 3056, Australia