BlueAnt









Welcome

Thank you for purchasing the BlueAnt X0i Portable Bluetooth Speaker. Please read through this manual to get the most out of your speaker.

Inside the box



Get to know your X0i speaker



	Item	Button	Function
	1	0	Power Button - Press and hold for about 1.5 seconds to power on or off
	2	0	Charge LED . Orange for charging. Green for fully charged
	3	0	Working mode LED. Slow blinking for pairing. Fast blinking for low battery
	4	*	Press Bluetooth button for 1.5 seconds to disconnect the current bluetooth device. For Duo Mode pairing, please see page 5.
	5	0	Volume - single click to reduce volume one step Volume - press and hold for 1.5 seconds to go back one track
	6	₪	Play button - click for play/pause. If incoming call click play to answer/ end call. To reject incoming call press and hold play button. Siri/Google - double click play button to starf/cancel Siri/ Google
	7	+	Volume + single click to increase volume one step. Volume + Press and hold for 1.5 seconds to go forward one track
	8		USB-C DV5V Input (behind the port cover)
2	9		Carry loop

Getting started

Power On/Off

Long press ① button to power on/off the speaker. The working mode led will flash white. Each time the speaker powers on, it will reset the volume to 50%. After 10 minutes with no connection, the X0i will automatically power off to conserve battery

Modes

Bluetooth Mode


A) Pairing

Power on the speaker and enter Bluetooth mode. The working mode LED will flash. On your smartphone search Bluetooth devices for the "BlueAnt XOI". Once connected, the speaker will announce it is "connected" and the indicator light will cease flashing.

3

B) Music C) Calls


+	Click to increase volume
+	Press and hold for 1.5 seconds to skip forward a track
\triangleright	Click to play/pause
_	Click to decrease volume
_	Press and hold for 1.5 seconds to skip back a track



D) Siri/Google

Double click to active/cancel Siri/Google voice dialing

E) Disconnect



4

F) Duo Mode

Dual speaker wireless stereo pairing for wide stereo sound stage. X0i Duo Mode will only work with another X0i.

- 1. Press and hold the power button on the two speakers to turn on the speaker. Make sure the speakers are not connected with any devices.
- 2. Choose one of the speakers as the master speaker. Press and hold the Bluetooth button for 3 seconds on the master speaker, until the speaker says "Duo Mode pairing", then release the button. Wait for 10 seconds. The two speakers will automatically connect each other. Search and connect X0i with Bluetooth on your phone, and your phone will be connected to the master speaker.

For Bluetooth pairing, search for "BlueAnt XOi" on your smartphone. If you receive a phone call while in Duo Mode, the call will only come through the master speaker. When in Duo Mode and you power off one speaker, both speakers will power off. When you power on the speakers, they need to be turned on individually. When both speakers are powered on, Duo Mode will automatically reconnect and you will hear "Duo Mode connected".

To disconnect Duo Mode, **press** and **hold** the Bluetooth button for 3 seconds on the Master speaker until you hear, "Duo Mode disconnected".

To clear Duo Mode pairing, **press** and **hold** the Bluetooth button for 3 seconds on the slave speaker, until the speaker says, **"Duo Mode cleared"**. Assuming direct line of sight, you should be able to achieve a range of over 5 metres between the two speakers.

When used indoors, the range will be affected by internal walls or obstacles between the speakers.

Charging

Please use the supplied USB-C cable to charge the X0i. When the X0i is charging the power light will stay orange. When fully charged the light will stay green. A full charge will take around 3 hours. Please close the port cover after you have charged the X0i.



SPLASHPROOF

The BlueAnt X0i features splashproof rating IP56. The X0i is only splashproof when the port cover is closed.

Important Safety Information

PLEASE READ THIS ENTIRE DOCUMENT CAREFULLY, BECAUSE IT CONTAINS IMPORTANT INFORMATION ABOUT THE USE OF BLUEANT DEVICES

WARNING - PROTECT YOUR HEARING

BLUEANT DEVICES CAN REACH VOLUMES ABOVE 100 DECIBELS

ONLY CHARGE WHEN DEVICE IS CLEAN AND DRY

Care and Handling

Your BlueAnt Bluetooth device is a precision engineered instrument. To ensure its ongoing performance, you should look after it as you would any quality consumer electronic product, and use it in accordance with the instructions. BlueAnt recommends that you take the following precautions. Avoid leaving your device in direct sunlight.

- Do not leave your device, or use your device, in any area where the temperature may exceed 50 degrees Centigrade, such as inside a closed car on a hot day. Remember that on a hot day, the temperature inside a closed car may be significantly higher than the outside air temperature.
- Do not leave your device, or use your device, in any area where the temperature is likely to drop below 0 degrees Centigrade (32 degrees Fahrenheit).
- Do not leave your device, or use your device, in any area exposed to humidity, dust, soot, other foreign objects, smoke, or steam as this may cause your device to malfunction.

PROLONGED USE AT HIGH VOLUMES MAY AFFECT YOUR HEARING CAPACITY AND MAY RESULT IN NOISE INDUCED HEARING LOSS (NIHL). TURN OFF THE POWER TO YOUR DEVICE WHEN NOT IN USE.

- Do not use any household or industrial grade detergents or cleaners to clean your device. If your device becomes dirty or smeared, in most instances a wipe with a dry or slightly damp cloth should be sufficient to clean it.
- Do not leave your Bluetooth device plugged into a wall for long periods after it is fully charged. BlueAnt does not recommend long periods of continued charging.
- Before charging your BlueAnt device, make sure that the AC outlet, adaptor and cable are not damaged. If you notice any abnormalities, seek advice from a qualified professional.

- If travelling internationally, ensure that your BlueAnt wall or car power adapter is approved for use in the country where you plan to use it and that the adapter voltage is suited to the local power supply.
- Should a fault develop with your BlueAnt product, contact BlueAnt for advice on how to proceed. Do not attempt to repair or alter any BlueAnt product yourself.

Approved Accessories

The use of accessories not approved by BlueAnt, including but not limited to batteries, antennas, wall adapters, car charger, ear gels and foam tips and convertible covers, may cause your BlueAnt device to malfunction or in the case of non approved electrical accessories may cause the device to exceed RF energy exposure guidelines.

Electromagnetic Interference

Nearly every electronic device is susceptible to electromagnetic interference (EMI) if inadequately shielded, electromagnetic configured for electromagnetic compatibility. Similiar to a mobile phone, your BlueAnt device is a low power transmitter/receiver and is covered by regulations pertaining to such devices. Turn off your BlueAnt device in any facility where posted notices instruct you to do so. These facilities may include hospitals or health care facilities that may be using equipment that is sensitive to external RF energy.

- When instructed to do so, turn off your BlueAnt device when on board an aircraft. Any use of a mobile device must be in accordance with applicable laws, regulations and airline crew instructions.
- If you use any other personal medical device, consult the manufacturer of your device to determine if it is adequately shielded from RF energy. Your doctor or physician may be able to assist you in obtaining this information.

• If you are in doubt about whether your BlueAnt device can be safely turned on or used, please consult an authorised person in the location you want to use your BlueAnt device. If no authorised person is available or you remain uncertain, BlueAnt recommends that you turn off your Bluetooth device and any mobile phones unless they are required in an emergency situation.

Recycling Bluetooth Accessories

Do not dispose of Bluetooth accessories, such as chargers, speakers, headphones or headsets with your household waste. In some countries or regions, collection systems are set up to handle electrical and electronic waste items, and may prohibit or restrict how such items are disposed of. Check the laws and regulations for your areas to determine how to properly dispose of such items.

BlueAnt Limited Global Warranty

This product is covered by BlueAnt's limited global warranty for one (1) year from the date of purchase by the first consumer purchaser of the product. Please refer to warranty.blueantwireless.com for full terms and conditions.

THANK YOU FOR CHOOSING A BLUEANT PRODUCT

For warranty and technical support, please email care@blueantwireless.com visit www.blueantwireless.com or call 1300 669 049

Register your BlueAnt product for warranty and new product updates at register.blueantwireless.com

Australian Consumer Law

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if goods fail to be of acceptable quality and the failure does not amount to a major failure.

BlueAnt Wireless

Suite 6, 861 Doncaster Road Doncaster, Vic. 3109 Australia

BlueAnt Limited Global Warranty

This product is covered by BlueAnt's limited global warranty for one (1) year from the date of purchase by the first consumer purchaser of the product. Please refer to warranty.blueantwireless.com for full terms and conditions.

THANK YOU FOR CHOOSING A BLUEANT PRODUCT

For warranty and technical support, please email care@blueantwireless.com visit www.blueantwireless.com or call 1300 669 049

Register your BlueAnt product for warranty and new product updates at register.blueantwireless.com

Australian Consumer Law

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if goods fail to be of acceptable quality and the failure does not amount to a major failure.

BlueAnt Wireless

Suite 6, 861 Doncaster Road Doncaster, Vic. 3109 Australia

BlueAnt



HELP & SUPPORT

Visit support.blueantwireless.com Email: care@blueantwireless.com Contact: 1300 669 049

Register your BlueAnt product for warranty and new product updates at register.blueantwireless.com



www.blueantwireless.com