BlueAnt




Z2iUser Manual



Welcome

Thank you for purchasing the BlueAnt X2i Portable Bluetooth Speaker. Please read through this manual to get the most out of your speaker.

Inside the box




1 x X2i Portable Speaker


1 x USB-C Cable

User Manual

1

Get to know your X2i speaker





Item	Button	Function
1	(0)	Power button - Short press to power on/off
2	0	Bluetooth Indicator
3	0000	Battery Indicator
4		AUX in Jack 3.5mm
5	0 %	USB-C Charge slot - USB cable supplied

	Item	Button	Function
	6	4	Volume Up - Short press Skip forward button - Long press
	7	>	Play/Pause button - Click to play/pause Double Click for Siri/Google Click to answer/end, Double Click to reject call
	8	0	Microphone
	9		Volume Down - Short press Skip backward button - Long press

Getting started

Power On/Off

Short press (a) button to power on/off the speaker. The indicator light will flash blue. Each time the speaker powers on it will reset to 50% volume. After 10 minutes with no connection, the X2i will automatically power off to conserve battery.

Modes

Bluetooth Mode

A) Pairing

Power on the speaker and enter Bluetooth mode. The light indicator will flash. On your smartphone search Bluetooth devices for the "BlueAnt X2i". Once connected, the speaker will announce it is "connected" and the indicator light will cease flashing.

B) Music

+	Click to increase volume
+	Press and hold for 1.5 seconds to skip forward a track
\rightarrow	Click to play/pause
_	Click to decrease volume
_	Press and hold for 1.5 seconds to skip back a track

C) Calls

>	Click to answer an incoming call
>	Click to end the active call
>	Double click to reject an incoming call or press and hold

D) Siri/Google

>	Double click to active/cancel Siri/Google voice dialing
---	---

E) Disconnect

Press and hold for 8 seconds to disconnect the current Bluetooth connection. The X2i
will prompt "disconnected". Then other Bluetooth devices can find and pair with the X2i.

F) Duo Mode

Dual speaker wireless stereo pairing for wide stereo sound stage. The X2i and X1i can be paired to each other in Duo Mode

- 1. Press the power button on the first speaker to turn the speaker "On".
- Press and hold the Volume + and Volume buttons on the first speaker until the speaker says "Duo Mode pairing" then release the buttons.
- 3. Press the power button on the second speaker to turn the speaker "On".
- 4. Press and hold the Volume + and Volume buttons on the second speaker until the speaker says "Duo Mode pairing" then release the buttons.
- Please wait until one speaker says "Duo Mode connected". This may take up to 1 minute. The speakers are now connected to each other.
- The speaker that says "Duo Mode connected" is the master speaker and this is the speaker that you should pair with your phone.

For Bluetooth pairing, search for "BlueAnt X2i" on your smartphone. If you receive a phone call while in Duo Mode, the call will only come through the master speaker.


When in Duo Mode and you power off one speaker, both speakers will power off. When you power on the speakers, they need to be turned on individually. When both speakers are powered on, Duo Mode will automatically reconnect and you will hear "Duo Mode connected".

To disconnect Duo Mode, press and hold Volume + and Volume - until you hear "Duo Mode disconnected".

To clear Duo Mode pairing, **press** and **hold** Volume + and Volume - until the speaker says "**Duo Mode cleared**". This takes about 8 seconds. Assuming direct line of sight, you should achieve be able to achieve a range of over 40 metres between the two speakers. When used indoors the range will be affected by internal walls or obstacles between the speakers.

AUX in Mode


Use 3.5mm audio cable to connect the speaker to an audio source (PC, MP3/MP4, mobile phone). When you plug the AUX cable into the X2i, it will automatically change to AUX in mode. When you unplug the AUX cable the X2i will change back to Bluetooth mode. The speaker will play the music from the audio source.



To change or control tracks, please use your music source when in AUX in mode.

Charging

Please use the supplied USB-C cable to charge the X2i. A full charge will take around 3 hours. Please close the port cover after you have charged the X2i.



SPLASHPROOF - The BlueAnt X2i features splashproof rating IP56. The X2i is only splashproof when the port cover is closed.

SAFETY INFORMATION AND WARRANTY TERMS

Important Safety Information

PLEASE READ THIS ENTIRE DOCUMENT CAREFULLY, BECAUSE IT CONTAINS IMPORTANT INFORMATION ABOUT THE USE OF BLUEANT DEVICES

WARNING - PROTECT YOUR HEARING

BLUEANT DEVICES CAN REACH VOLUMES ABOVE 100 DECIBELS

ONLY CHARGE WHEN DEVICE IS CLEAN AND DRY

Care and Handling

Your BlueAnt Bluetooth device is a precision engineered instrument. To ensure its ongoing performance, you should look after it as you would any quality consumer electronic product, and use it in accordance with the instructions. BlueAnt recommends that you take the following precautions. Avoid leaving your device in direct sunlight.

- Do not leave your device, or use your device, in any area where the temperature may exceed 50 degrees Centigrade, such as inside a closed car on a hot day. Remember that on a hot day, the temperature inside a closed car may be significantly higher than the outside air temperature.
- Do not leave your device, or use your device, in any area where the temperature is likely to drop below 0 degrees Centigrade (32 degrees Fahrenheit).

• Do not leave your device, or use your device, in any area exposed to humidity, dust, soot, other foreign objects, smoke, or steam as this may cause your device to malfunction.

PROLONGED USE AT HIGH VOLUMES MAY AFFECT YOUR HEARING CAPACITY AND MAY RESULT IN NOISE INDUCED HEARING LOSS (NIHL). TURN OFF THE POWER TO YOUR DEVICE WHEN NOT IN USE.

- Do not use any household or industrial grade detergents or cleaners to clean your device. If your device becomes dirty or smeared, in most instances a wipe with a dry or slightly damp cloth should be sufficient to clean it.
- Do not leave your Bluetooth device plugged into a wall for long periods after it is fully charged. BlueAnt does not recommend long periods of continued charging.

8

- Before charging your BlueAnt device, make sure that the AC outlet, adaptor and cable are not damaged. If you notice any abnormalities, seek advice from a qualified professional.
- If travelling internationally, ensure that your BlueAnt wall or car power adapter is approved for use in the country where you plan to use it and that the adapter voltage is suited to the local power supply.
- Should a fault develop with your BlueAnt product, contact BlueAnt for advice on how to proceed. Do not attempt to repair or alter any BlueAnt product yourself.

Approved Accessories

The use of accessories not approved by BlueAnt, including but not limited to batteries, antennas, wall adapters, car charger, ear gels and foam tips and convertible covers, may cause your BlueAnt device to malfunction or in the

case of non approved electrical accessories may cause the device to exceed RF energy exposure guidelines.

Electromagnetic Interference

Nearly every electronic device is susceptible to electromagnetic interference (EMI) if inadequately shielded, electromagnetic configured for electromagnetic compatibility. Similiar to a mobile phone, your BlueAnt device is a low power transmitter/receiver and is covered by regulations pertaining to such devices. Turn off your BlueAnt device in any facility where posted notices instruct you to do so. These facilities may include hospitals or health care facilities that may be using equipment that is sensitive to external RF energy.

- When instructed to do so, turn off your BlueAnt device when on board an aircraft. Any use of a mobile device must be in accordance with applicable laws, regulations and airline crew instructions.
- If you use any other personal medical device, consult the manufacturer of your device to determine if it is adequately shielded from RF energy. Your doctor or physician may be able to assist you in obtaining this information.
- If you are in doubt about whether your BlueAnt device can be safely turned on or used, please consult an authorised person in the location you want to use your BlueAnt device. If no authorised person is available or you remain uncertain, BlueAnt recommends that you turn off your Bluetooth device and any mobile phones unless they are required in an emergency situation.

Recycling Bluetooth Accessories

Do not dispose of Bluetooth accessories, such as chargers, speakers, headphones or headsets with your household waste. In some countries or regions, collection systems are set up to handle electrical and electronic waste items, and may prohibit or restrict how such items are disposed of. Check the laws and regulations for your areas to determine how to properly dispose of such items.

BlueAnt Limited Global Warranty

This product is covered by BlueAnt's limited global warranty for one (1) year from the date of purchase by the first consumer purchaser of the product. Please refer to warranty.blueantwireless.com for full terms and conditions

THANK YOU FOR CHOOSING A BLUEANT PRODUCT

For warranty and technical support, please email care@blueantwireless.com visit www.blueantwireless.com or call 1300 669 049

Register your BlueAnt product for warranty and new product updates at register.blueantwireless.com

Australian Consumer Law

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if goods fail to be of acceptable quality and the failure does not amount to a major failure.

BlueAnt Wireless Suite 6, 861 Doncaster Road Doncaster, Vic. 3109 Australia

Notes



100% AUSTRALIAN DESIGNED & OWNED



HELP & SUPPORT

Visit support.blueantwireless.com
Email: care@blueantwireless.com
Contact: 1300 669 049

Register your BlueAnt product for warranty and new product updates at register.blueantwireless.com

f ☑ ¥ ‱ **v** www.blueantwireless.com